

Go Power!®

30AMP TRANSFER SWITCH



EFFICIENT AUTOMATIC POWER SWITCHING



MODEL #: GP-TS-30

The Go Power! Transfer Switch 30 amp (GP-TS-30) provides automatic power switching between two separate 120 volt AC input sources. An automatic transfer switch is usually installed to allow both your inverter and shore power to alternatively feed the circuits and prevent AC back feed.

The Go Power! GP-TS-30 is a 30 amp AC switch that automatically connects shore power (when available) to your breaker panel. When unplugged from power, it then connects your inverter output to power your circuits.

SPECIFICATIONS

Voltage Rating	120
Current Rating (line)	30 Amps
Dominant Source	Generator (20-45 sec delay)
Open Neutral Protection	No
Reverse Polarity Protection	No
Safety Interlocks	Mechanical & Electrical
Under Voltage Protection	No
Over Voltage Protection	No
Multi Mode Surge Protection	No
Total Surge Energy Rating	None
Total Surge Current Rating	None

MECHANICAL

Length	9.65 in / 245.11 mm
Width	7.28 in / 184.91 mm
Height	4.75 in / 120.65 mm
Weight	3 lbs / 1.36 kg

Specifications may be subject to change. Product may not be exactly as shown.
Specifications subject to local environmental conditions.



30AMP TRANSFER SWITCH



Specifications may be subject to change. Product may not be exactly as shown.
Specifications subject to local environmental conditions.